



HDMI Extender Kit with 2 CAT5 Outputs Up to 100M

The Comprehensive CHE-330DC HDMI Extender is an extender for HDMI signals up to 100 meters. In addition, the receiver has 2 CAT5 outputs to daisy-chain to another receiver to achieve even longer distances and more outputs. Receiver could be chainable up to 31 layers with distance of 3.1KM. It also could be cascaded to a total of up to 100 displays. The HDMI extender is HDMI 1.3 compliant and HDCP compatible. Extender has a transmission range up to 100M at 1080p. Plug and play for easy operation. Unit is covered by our 2 year warranty.



Features

- Extends HDMI signal over one CAT5/5e/6 cable
- Including transmitter and receiver unit
- Receiver built in 1 x HDMI output and 2 x CAT5 output daisy-chainable to another receiver for longer distance and multiple displays
- Receiver could be chainable up to 31 layers with distance 3.1KM, also cascadeable, total up to 100 displays ~
- HDMI 1.3 compliant
- HDCP compatible
- Transmission range up to 100M at 1080p
- Plug and play for easy operation
- 2 Year warranty

Specifications

Input Transmitter: HDMI A Female
Output Receiver: HDMI A Female, RJ45 x 3
Link interface: RJ45 Female
Transmission Distance: 100M
Power Consumption: Transmitter 860mA, Receiver 950mA
Power Supply: DC 5V 2 amp x 2
Temperature: Operation: 0°C to 55°C, Storage: -20°C to 85°C,
Humidity: up to 95%
Dimensions: Transmitter 2.65 x 5.5 x 1.06, 67mm x 140mm x 27mm, Receiver 2.65 x 6.1 x 1.06, 67mm x 155mm x 27mm W x H x D
Weight: Transmitter .5 lbs, Receiver .75 lbs, total 1.25lbs.
Warranty: 2 Years

CHE-330DC HDMI Extender Kit with 2 CAT5 Outputs Up to 100M